



## INVERTER Axil CW1000/1200/2000/2200

### KEY FEATURES

- High Frequency Design
- Narrow/Wide Input Range Selection
- Build-in AC Charger
- Generator Compatible
- Optional LED/LCD Panel
- Cold Start Function
- Wall-Mount Compatible



### SPECIFICATION

Model Name	Axil CW 1000	Axil CW 1200	Axil CW 2000	Axil CW 2200
Capacity	1000VA/600W	1200VA/720W	2000VA/1200W	2200VA/1320W
<b>Input</b>				
Nominal Voltage	220-240Vac			
Voltage Range	Wide mode: 100VAC-280VAC Narrow mode: 190VAC-260VAC			
Frequency	50Hz/60Hz (Auto Sensing)			
<b>Output</b>				
Nominal Voltage(Batt.mode)	220-240Vac			
Frequency(Batt.mode)	50Hz/60Hz			
Waveform (Batt.mode)	Simulated Sine wave			
Transfer Time	15-20ms			
<b>Battery</b>				
Battery Voltage	12V	12V	24V	24V
Maximum AC Charge Current	10A	20A	10A	10A
<b>Indicators</b>				
Display	LED /LCD			
Alarm	Batt. Mode, low battery, overload, fault, etc.			
<b>Management</b>				
Auto Recharge	Yes			
Auto Restart	Yes			
Power Management Software	Yes			
<b>Physical</b>				
Dimension(W x H x D)(mm)	250 x 90 x 265			
Net Weight (kg)	1.9	2.05	2	2.2
<b>Environment</b>				
Operating Humidity	0-90% non-condensing			
Operating Temperature	0-40°C			